

## ACCESSORIES

### AUXILIARY I/O CARD

#### **Retransmit**

- 2 Analog output channels
- Scalable 0-10V dc or 0-20mA with up to 15 Vdc compliance voltage
- Each channel may be assigned either the RMS or AVG value of the load voltage, load current, or true instantaneous load power

#### **Digital I/O**

- 2 Digital inputs (TTL compatible, pull up to 5V through a 10KΩ resistor)
- 2 Digital Outputs (Relay driver transistor based, Open collector that sinks up to 48 Vdc at 150 mA)

### FIELD BUS INTERFACE

MODBUS RTU (RS-485), MODBUS TCP (Ethernet), DeviceNet, or EtherNet/IP, or PROFINET. Simplify your cabling, eliminate A/D conversion error, and gain access to monitor information.

In the model number, use:

- S for Modbus RTU (RS-485)
- D for DeviceNet
- I for EtherNet/IP
- E for Modbus TCP (Ethernet)
- N for PROFINET

### REMOTE DISPLAY

- Controller display is mountable in a 1/4 DIN cutout
- UL-type 1 & 12 ratings, IP65
- Outside Dimensions: 4.156 [105.6] x 4.156 [105.6]
- Display Mounting Kit includes: Gasket, custom mounting brackets with screws, shielded cable, circuit board retainer
- Sizes: 25 ft [7.62m] (CCI P/N: SMAFUSION-RD25)  
5 ft [1.52m] (CCI P/N: SMAFUSION-RD5)

### USB CABLE

- 15 ft [4.92m] USB Cable (CCI P/N: 0058004-0000-15)

### FUSES AND OTHER ACCESSORIES

- A wide range of fuses and fuse blocks are available.
- Please contact factory for fuse sizing and any other accessory needs and we would be happy to accommodate you.

## CONTACT/ORDERING INFORMATION

TEL: (952) 474-6200 | (800) 765-2799  
FAX: (952) 474-6070 | [www.ccipower.com](http://www.ccipower.com)  
8077 Century Blvd, Chanhassen, MN 55317, USA

